

10-1300
FISH & RICHARDSON P.C.

October 12, 2000

A & CD
225 Franklin Street
Boston, Massachusetts
02110-2804

Telephone
617 542-5070

Facsimile
617 542-8906

Web Site
www.fr.com

Attorney Docket No.: 02103-390001

Box Patent Application
Commissioner for Patents
Washington, DC 20231

Presented for filing is a new original patent application of:

Applicant: Paul E. Beckmann, Santiago Carvajal and Christopher H. Perry

Title: INTERACTIVE SOUND REPRODUCING

Enclosed are the following papers, including those required to receive a filing date under 37 CFR §1.53(b):

	<u>Pages</u>
Specification	27
Claims	15
Abstract	1
Declaration	2
Drawing(s)	13

Enclosures:

— Postcard; and

— Appendix

Basic filing fee	\$710
Total claims in excess of 20 times \$18	\$414
Independent claims in excess of 3 times \$80	\$960
Fee for multiple dependent claims	\$0
Total filing fee:	\$2084

CERTIFICATE OF MAILING BY EXPRESS MAIL

Express Mail Label No. EL 624 275 964 US

I hereby certify under 37 CFR §1.10 that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee with sufficient postage on the date indicated below and is addressed to the Commissioner for Patents, Washington, D.C. 20231.

October 12, 2000
Date of Deposit

Samantha Bell
Signature

Samantha Bell
Typed or Printed Name of Person Signing Certificate

BOSTON

DALLAS

DELAWARE

NEW YORK

SAN DIEGO

SILICON VALLEY

TWIN CITIES

WASHINGTON, DC

FISH & RICHARDSON P.C.

Commissioner for Patents

October 12, 2000

Page 2

A check for the filing fee is enclosed. Please apply any other required fees or any credits to deposit account 06-1050, referencing the attorney docket number shown above.

If this application is found to be incomplete, or if a telephone conference would otherwise be helpful, please call the undersigned at (617) 542-5070.

Kindly acknowledge receipt of this application by returning the enclosed postcard.

Please send all correspondence to:

CHARLES HIEKEN
Fish & Richardson P.C.
225 Franklin Street
Boston, MA 02110-2804

Respectfully submitted,

FISH & RICHARDSON P.C.



Charles Hieken

Reg. No. 18,411

Attorneys for Application Owner

Enclosures

CPH/dmm

20135821.doc

003107 2268950

**APPLICATION FOR
UNITED STATES PATENT**

TITLE: Interactive Sound Reproducing
APPLICANTS: Paul E. Beckmann, Santiago Carvajal,
and Christopher H. Perry

CERTIFICATE OF MAILING BY EXPRESS MAIL

Label No.: EL 624 275 964US

I hereby certify under 37 CFR §1.8(a) that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee with sufficient postage on the date indicated below and is addressed to the Commissioner for Patents, Washington, D.C. 20231.

Date of Deposit

October 12, 2000

Signature

Samantha Bell

Typed or Printed Name of Person Signing Certificate

Samantha Bell

002101 72268960

INTERACTIVE SOUND REPRODUCING

CROSS-REFERENCE TO RELATED APPLICATIONS

Not applicable.

STATEMENT REGARDING FEDERALLY SPONSORED

RESEARCH OR DEVELOPMENT

Not applicable.

BACKGROUND OF THE INVENTION

The invention relates to interactive sound reproducing and more particularly to sound reproducing from computer compact disk (CD) drives, network radio stations, broadcast radio stations, and digitally encoded computer files.

It is an important object of the invention to provide improved interactive sound reproducing.

BRIEF SUMMARY OF THE INVENTION

According to the invention, an audio system includes a sound reproduction device for producing audible sound from audio signals. The sound reproduction device includes a radio tuner, a powered speaker and a connector for connecting the sound reproduction device with a computer. The computer provides audio signals from a plurality of sources. The sources include a computer CD player, digitally encoded computer files stored on the computer, and a computer network connected to the computer. The sound reproduction device includes control buttons for controlling at least one of the computer CD player, the digitally encoded computer files and the computer network.

In another aspect of the invention, an audio system includes a sound reproduction device for producing audible sound from audio signals. The sound reproduction device includes an enclosure, enclosing a radio tuner and a powered speaker. The audio system further includes a connector for connecting the sound reproduction device with a computer, the computer for providing audio signals from a computer CD player, from digitally encoded computer files, and from a computer network.

In another aspect of the invention, an audio system includes a sound reproduction device for reproducing audible sound from audio signals, a computer coupled to the sound reproduction device for receiving the audio signals from a computer network, the audio signals being transmitted from an alternatively selectable plurality of network addresses, and a remote control device, for communicating commands to the sound reproduction device, the remote control device comprising a plurality of indicator buttons. An indicating one of the indicator buttons causes the computer to select a preassigned one of the network addresses.

In another aspect of the invention, an audio system includes a computer system and a sound reproduction system for reproducing audible sound from audio signals. The audio signals come from a plurality of selectable sources. A method for switching the sound reproduction system from an unpowered state to a powered state includes transmitting a control signal from the sound reproduction system to the computer

system. If the computer system responds to the control signal, the method determining by the sound reproduction device that the computer system is in a responsive state and

If the computer system does not respond to the control signal, determining by the sound reproduction device that the computer system in an unresponsive state.

In another aspect of the invention, a radio receiver has a number n of preset indicators. A method for assigning broadcast frequencies to individual preset indicators includes determining the location of the radio receiver and scanning the frequency spectrum to determine the strongest signals.

In another aspect of the invention, a sound system includes a sound reproduction device coupled to a computer system and a remote control device, for transmitting encoded control commands to the sound reproduction device. A method for decoding the commands includes receiving, by the sound reproduction device, one of the encoded control commands, and decoding, by the sound reproduction device, the one received control command, and executing, by the sound reproduction device, the one received control command. In the event that the one received control command is not decodable or is not executable by the sound reproduction device, the method includes transmitting the encoded control command to the computer system.

In another aspect of the invention, an audio system includes a sound reproduction device for reproducing audible sound from audio signals from a plurality of sources. The

sources including a radio tuner and at least one of a CD containing a plurality of individually indicatable tracks, a plurality of individually indicatable network addresses, and a plurality of individually indicatable digitally encoded files stored on a digital storage device. The audio system includes a source selector for selecting from the plurality of sources, a source of audio signals to be reproduced by the sound reproduction device and a control signal input device. If the selected source is the radio tuner, an activation of the control signal input device changes the tuning frequency of the radio tuner; if the selected source is the CD, an activation of the control signal input device changes the indicated CD track or play position within a track; and if the selected source is the selectable network addresses, an activation of the control signal device changes the indicated network address.

In another aspect of the invention, a method of operating an audio system adapted to reproduce sound from a plurality of digitally encoded files which contain identifying characteristics includes assigning a value of one of the identifying characteristics to a preset indicator; on the indicating of the preset indicator, searching the plurality of files for the value of the one identifying characteristic; and selecting for reproduction the digitally encoded files having the value.

In still another aspect of the invention, a method for selecting from a plurality of audio signal sources having

identifying characteristics, a single audio signal source, includes specifying a value of one of the identifying characteristics; determining, by a computer, which of the audio signal sources have the value for the one
5 characteristic; and selecting a single audio source from the plurality of audio signal sources.

According to another aspect of the invention, a method gives multiple sets of values to a single set of presets being used with a single source. The method changes the set of
10 values by clicking on a graphic, such as a right or left arrow on the screen display, to bring up a new set of values for the presets. Typically, any one of the set of values is selectable by either clicking with the pointing device on the appropriate preset on the screen, pressing the selected preset
15 on the remote, or pressing the preset on the radio.

Other features, objects, and advantages will become apparent from the following detailed description, which refers to the following drawings in which:

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of a first configuration of a networked sound system according to the invention;

FIG. 2 is a block diagram of a second configuration of a networked sound system according to the invention;

FIG. 3 is a block diagram of the interface unit of FIGS.
1 and 2;

FIG. 4 is a diagram helpful in explaining the logical database relationships of recorded units and assemblages of recorded units;

FIG. 5 is a sound reproduction device control panel according to the invention;

FIG. 6 is a representation of an interface screen on a computer display in accordance with the invention;

FIG. 7 is a flow diagram for assigning broadcast radio frequencies to the preset buttons according to the invention;

FIG. 8 shows the buttons on the remote control device;

FIGS. 9A, 9B, 9C and 9D are schematic circuit diagrams of circuitry in a radio that implement elements 12, 14 and 16 of the system of FIG. 2; and

FIG. 10 is an implementation of the interface unit 54 of FIG. 2.

DETAILED DESCRIPTION OF THE INVENTION

With reference now to the drawings and more particularly to FIG. 1, there is shown a first configuration of a networked sound system according to the invention. Sound reproduction device 10 includes an AM/FM tuner 12, audio signal processing circuitry 14, control electronics circuitry 16 for controlling the tuner and signal processing circuitry, a remote control device 17 for communicating commands to control electronics circuitry 16, and an electroacoustical transducer 18. An auxiliary (hereinafter ``aux'') input 13 typically implemented as a signal jack permits the sound reproduction device to

receive audio signals from outside sources, such as portable CD players. Computer system (PC) 20 includes a bus 22 which interconnects various computer system components and carries data and control signals between them. Hardware components may include CPU 24, RAM 26, CD player 28, a mass storage device, such as a hard disk 30, a network interface card 32, and a sound card 33. Computer system 20 also includes a number of external connectors for connecting bus 22 with various external devices. A first external connector 34 connects to an external display 36. A second external connector 38 connects to an external input device such as a mouse 40. A third external connector 42 connects to a keyboard 44. A fourth external connector 46 connects network interface card 32 to a local or wide area network for transmitting to and receiving signals from remote devices that are connected to the local or wide area network. A fifth external connector 43 connects to external mass storage device 45. Stereo jack 48 connects sound card 33 to radio audio signal processing circuitry 14 through analog input terminal 49. Audio system control connector 50 connects bus 22 to control electronics circuitry 16 through digital input terminal 51.

Referring now to FIG. 2, there is shown a second configuration of a networked audio system according to the invention. The elements of FIG. 2 are the same as the elements of FIG. 1, with some exceptions. Sound card 33 of FIG. 1 is not needed in this configuration. Stereo jack 48

and the audio system control connector 50 of FIG. 1 are replaced by a bus interface connector 52, which connects to an interface unit 54. The interface unit 54 connects to audio signal processing circuitry 14 through analog terminal 49 and to control electronics circuitry 16 through digital terminal 51. Interface unit 54 will be described in more detail in connection with a subsequent figure.

A networked audio system which contains both the powered speaker and the radio tuner in a single enclosure is advantageous over conventional audio systems which house the speakers and radio tuner in separate enclosures, because the system can then be configured to occupy less space in a work area.

Referring to FIG. 3, there is shown interface unit 54 in more detail. Signal line 56 from interface connector 52 is connected to logic circuitry 58. Logic circuitry 58 is coupled to D/A converter 60 which is connected to analog terminal 49 by analog signal line 62. Analog terminal 49 is in turn connected to audio signal processing circuitry 14. Logic circuitry 58 is connected to digital terminal 51 by digital signal line 64. Digital terminal 51 is in turn connected to control electronics circuitry 16. If bi-directional flow of analog signals is desired, a second analog signal path is provided. The second analog signal path includes a signal line between audio signal processing circuitry 14 and a second analog terminal 66; a second analog signal line 68 connecting second analog terminal 66 and an A/D

converter 70; and a signal line connecting A/D converter 70 and logic circuitry 58.

In operation, logic circuitry 58 determines if transmissions on signal line 56 from bus 22 are intended for sound reproduction device 10. If signals on bus 22 are intended for sound reproduction device 10, logic circuitry 58 determines whether the signals are control signals or audio information. If the signals are control signals, logic circuitry 58 transmits signals to digital terminal 51 over digital signal line 64. If signals are audio information, logic circuitry transmits signals to D/A converter 60 which converts the digital signal to an analog audio signal. Analog audio signal is then transmitted over analog signal line 62 to analog terminal 49 and then to audio signal processing circuitry 14. The digital signal path including control circuitry 16, digital terminal 51, digital signal line 64, logic circuitry 58 signal line 56, and interface connector 52 is constructed and arranged to transmit signals bidirectionally, so that control signals originating at control circuitry 16 can be transmitted to computer bus 22 for processing by CPU 24. If bidirectional flow of analog circuitry is desired, analog signals may be transmitted from audio signal processing circuitry 14 to second analog terminal 66, and to A/D converter 70, where it is converted to a digital signal that is then transmitted to logic circuitry 58.

In one implementation, sound reproduction device 10 is a Wave® radio equipped with an appropriate communications ports,

available from the Bose Corporation of Framingham, Massachusetts. Computer system 20 may be a conventional multimedia personal computer.

There are typically three implementation arrangements for interface unit 54. One alternative is to implement interface unit 54 as a module in computer system 10. In this arrangement, interface unit 54 is implemented as a circuit board that connects internally to bus 22 (so that interface connector 52 is internal to the computer, and is physically connected to an expansion slot in the computer), signal lines 62, 64, and 68 are implemented as cables, and digital terminal 51, analog terminal 49 (and second analog terminal 66, if present) are external ports for the sound reproduction device 10.

A second alternative is to implement interface unit 54 as an intermediate, separate unit, typically integrated with cables which implement signal lines 62, 64, 68, and 56. In this arrangement, interface connector 52 is an external computer port, and digital terminal 51, analog terminal 49 (and second analog terminal 66, if present) are external ports for the sound reproduction device 10.

A third alternative is to implement interface unit 54 as a module, such as a circuit board, in the sound reproduction device 10. In this arrangement, sound reproduction device 10 has an external port to accommodate a cable that implements signal line 56, and the remaining signal lines and terminals are internal to sound reproduction device 10.

A networked sound system according to the invention may have a number of operating modes. In a first mode, sound reproduction device 10 operates as a standalone sound reproduction device (hereinafter ``standalone mode''), similar to a conventional radio or hi-fi receiver. Operating in this mode, sound reproduction device operates independently of computer system 20, and even operates if computer system 20 is not running. In a second operating mode (hereinafter ``sound effects mode''), sound reproduction device 10 operates as conventional computer speakers, reproducing sounds that are incidental to programs running on computer system 20. Examples may be sound effects in computer games, audible alarms and warnings, indicating, for example, that the computer system has received electronic mail. In a third operating mode (hereinafter ``audio system mode'') sound reproduction device 10 operates as a processor and reproducer of audio signals from a variety of sources, including networked sources and components of the computer system 20.

When the system is operating in the sound effects mode and the audio systems mode, the operation of the components of the system is controlled by a software program running on computer system 20. For efficient use of computer resources, the software program may be divided into two program modules, one of which provides communications between components of computer system 20 and sound reproduction device 10, and a second which accesses sound sources as described below. Additionally, the first program module can contain

instructions such that it automatically activates the second program module if it detects a communication from sound reproduction device 10 to computer system 20 that requires that the second module be running.

5 Operating in standalone mode, sound reproduction device 10 is controlled as, and operates as a standard radio or receiver. On/off, tuning, and volume control are all either entered by control buttons or dials that are connected electronically to control electronics circuitry 16, or by
10 remote control device 17.

Operating in sound effects mode, sound reproduction device 10 is controlled as, and operates as, standard amplified computer speakers having an on/off switch and volume control.

15 Operating in audio systems mode, sound reproduction device 10 reproduces sound from tuner 12, aux input 13, digital audio signals stored in RAM 26, hard disk 30, or external mass storage device 45; audio signals received from sources connected to the local or wide area network connected
20 to network interface 32; and other sources such as CD player 28 (which can be a component of computer system 20 as shown, or which can be a separate component, connected directly to sound reproduction device 10). The source or sources of the audio signals is controlled by a computer program running on
25 computer system 20.

If sound reproduction device 10 is in the ``off'' state, and is turned ``on'' either by pressing the ``on'' or ``power''

button or a button or indicator performing an equivalent function, or by pressing the corresponding button on remote control device 17, control electronics circuitry 16 detects whether computer 20 is connected, and if connected, in the
5 ``on'' or ``off'' state. If computer 20 is not connected or is in the ``off'' state, sound reproduction device 10 operates in standalone mode, and sound reproduction device begins reproducing audio signals from the last internal audio signal source (in one implementation, either AM or FM signals from
10 AM/FM tuner 12, or signals from aux input 13). If computer 20 is in the ``on'' position and the second program module (as described above in the discussion of ``Operating Modes'') is not running, the first program module activates the second program module, and the sound reproduction device begins
15 producing signals from the last audio signal source, as described above in the discussion of ``audio systems mode.'' If computer 20 is in the ``on'' position and the second program module is running, the sound reproduction device begins producing signals from the last audio signal source.

20 Recorded on hard disk 30 or external mass storage 45 may be information about typically either AM broadcast, FM broadcast, broadcast radio stations available to the reproduction device 10 through tuner 12. Typically, availability is determined by a combination of proximity to
25 and direction to the broadcast site, directionality and power of the broadcast signal, obstructions (such as tall buildings and mountains), and competing signals, especially those in

nearby frequency bands. The list of radio stations available to the reproduction device may be assembled in a number of ways. In a simple form, the user may manually tune a radio station and manually enter into the data base identifying information about the radio station. In more sophisticated forms, the reproduction device may automatically scan the broadcast frequency spectrum and assemble a list of available radio stations by noting the frequency and by measuring signal strength of received signals, or a suggested list of radio stations, based on location information such as zip code, or can be compiled by a resource (such as the vendor of the reproduction device or a commercial information assembler). Information about each radio station can also be collected and stored. Such information can include: station broadcast frequency; station call letters and/or other identifiers; station format (news, type of music, location, and others).

Information about radio stations that are accessible over the local or wide area network (hereinafter web radio stations) is also acquired and stored. This information may be acquired through search engines, by commercially available listings from suppliers such as vTuner (vTuner.com), or assembled by the user. Information about web radio stations typically include a station identifier, a network address, a category (e.g. news, rock, jazz, sports, classical), and a location of origination.

The information about broadcast radio stations and web radio stations, respectively, may be organized and sorted based on any of the information types mentioned above.

In addition to reproducing sound, a networked sound system according to the invention can record, on hard disk 30 or external mass storage device 45. Recording can be done simultaneously with sound reproduction, or in the ``background.'' Sound is recorded in units, and the units are identified and information about the units are recorded in a data base. For example, a typical recording unit is a track on a CD. The information about each unit (track) may include title, composer, artist, category (e.g. classical, rock, blues). The information may be obtained automatically or by user intervention from commercially available internet sources and/or may be entered or edited by the user. Additionally, for other types of recording units, the information may be of other types (such as for radio broadcasts a station and a time interval; for athletic events the date and participating teams; for cultural events the date, performer, composer; and others). For convenience, recorded units and assemblages of recorded units are referred to as ``music files'' even though the recorded units are not necessarily recordings of music.

Referring now to FIG. 4, there is shown a diagram that will be used to discuss the logical relationships of recorded units and assemblages of recorded units. Recorded units 110-1 through 110-n each contain data representing the recorded sound and information about the recorded sound. Information

could include the artist, the composer, and the type of music. A first type of assemblage of recorded units is an ``album'' represented here as items 112a, 112b, 112c. Albums 112a, 112b, and 112c may also have associated with them information similar to the information about the recorded units, such as artist, composer, and type of music. Albums may include recorded units that have different composers, artists, or type of music.

A second type of assemblage includes recorded units with common identifying characteristics, sometimes referred to as common ``metadata'' values. ``Metadata'' values are typically included in file header information of music files in many popular music file formats. Metadata values may include the artist, the composer, the type of music, and others. For example, element 114 represents an assemblage that includes all albums (112a and 112b) that include a track performed by a predetermined artist and all tracks performed by that artist. Album 112b is included in the assemblage, even though it may include only one track 110-7 performed by that artist and even though that album may contain tracks that are performed by other artists. In other embodiments, the assemblage may be set up such that only tracks performed by the artist are included in the assemblage. Similarly, assemblage 114 may represent an assemblage of all recorded units written by a common composer or containing a common type of music.

For example, if an assemblage contains music files having a common composer metadata value of ``Beethoven'', each time

the assemblage is requested, a computer database program may search all the music files for the metadata value of ``Beethoven'' as the composer. In this manner, each time a new music file is recorded with ``Beethoven'' as the composer, it is automatically added to the assemblage. In other words, this second type of assemblage may be said to be dynamically constructed.

A third type of assemblage is represented by playlist 116. In this example, playlist 116 includes artist assemblage 114, album 112c, and track 110-n.

Information about recorded units, playlists and other assemblages, broadcast radio stations, computer network accessible radio stations is stored in a data base stored in RAM 26 mass storage device 30 or external mass storage device 45. In one implementation, a record of the data base may correspond to a broadcast radio station, a web radio station, or a recorded unit. The fields of the records representing broadcast radio stations may contain information such as call letters, broadcast frequency, station format, or signal strength. The fields of record representing computer network accessible radio stations may include a identifiers, network addresses, locations, and station formats. The fields of record representing recorded units may include the metadata values as described above.

Referring to FIG. 5, there is shown a control panel from sound reproduction device 10. Preset buttons 72a - 72f each have a broadcast frequency associated with it. When that

button is depressed by the user, the control electronics circuitry causes the control electronics circuitry (of FIG. 1) to cause the tuner 12 to tune to the frequency associated with that preset button.

5 In addition to associating broadcast frequencies to the identifiers, a networked sound system according to the invention can assign other entities to the preset button. Other entities can include web radio network addresses, playlists; or recorded units, such as individual CD tracks, or
10 other assemblages of recorded unit as described above.

In a networked sound system according to the invention, there are at least three ways of activating the preset buttons. The buttons of FIG. 5 can be depressed; corresponding buttons on remote control device 17 can be
15 depressed; or a graphical representation of a corresponding preset button that is caused to appear on external display 36 by a computer program may be selected by operation of mouse 40. Hereinafter, the term ``preset indicator'' will be used to denote the preset buttons on the control panel (FIG. 5), the
20 preset buttons on the remote control device (FIG. 8), or the graphical representation of the preset buttons on the display (FIG. 6). In one embodiment, there is a one to one correspondence between the preset buttons on the control panel of the sound reproduction device, the preset buttons on remote
25 control device 17, and the graphical representation of preset buttons appearing on external display 36. Activating a preset button on control panel of FIG. 5, the corresponding preset

button on remote control device 17, or the graphical representation of the preset button on external display 36 causes the same entity to be selected. For each different source, a different entity may be assigned to each preset button, as will be described below. There may also be multiple sets of values to a single set of presets being used with a single source as discussed above. For example, there may be multiple sets of FM and/or AM radio stations.

A common user interface screen is caused to appear on external display, with some of the portions of the screen having different identifying legends. Referring to FIG. 6, there is shown a user interface screen. Source selection region 78 has graphical regions enabling the user to select the audio signal source. In this implementation, a CD, AM broadcast radio, FM broadcast radio, Web Radio, and Music Files (e.g. recorded units) can be selected. In current selection region 88, information about the selection currently displayed is shown. In available selections region 90, information about the available selections is shown. In preset section 92, six graphical figures, corresponding to the six preset buttons shown in FIG. 6 are displayed. ``Tune'' graphical figures 79 are discussed below in the discussion of FIG. 8.

The information displayed in the available selections region 90 may be ordered based on any of the metadata values. For example, the list of FM stations of FIG. 6 can be ordered in by station ID as shown, or could be ordered by broadcast

frequency, or by category (station format). Ordering the list of stations in different manners enables the user to more easily select the music to be reproduced from the list of available selections, especially if the number of available selections is large. For example, if the user has selected 5 ``web radio'' as the source, there may be hundreds of entries displayed in the available selections region. If the user wants to listen to a particular type of music, for example jazz, the user can order the list of available web radio stations by station format, and scroll through the list and 10 listen to web radio stations until a suitable station is found. Scrolling through the list can be done by using the arrow keys on the computer keyboard, the ``tuning'' buttons 128 (FIG. 5) on the control panel, or the corresponding buttons 147 (FIG. 8) on the remote control device.

The entities that can be assigned to the preset buttons are dependent on the audio source selected by activating the appropriate graphical figure in the source selection region 78. If the CD source has been activated, the preset buttons 15 are not active. If the AM broadcast or FM broadcast graphical figure have been activated, broadcast frequencies in the AM and FM broadcast bands, respectively, can be assigned to the preset buttons. For convenience and ease of identification, the call letters may also be displayed on the graphical 20 representation. If the web radio audio source has been activated, a URL of a web radio website are assigned to the preset buttons. For ease of identification, the name, or 25

other identification about the website is typically displayed on the preset buttons.

If the music files audio source has been selected, any assemblage, as discussed above, of recorded units can be assigned to a preset buttons. For combinations of recorded units, a play mode may also be assigned to the preset button. "Play modes" may include sequential, in which the recorded units are played in the order they appear in the database (typically, for example, for an album, this means in the order the individual "cuts" appear on the album), "shuffle" or "random," in which the recorded units are played in a random order, and "repeat" either single cuts or a sequence of cuts.

In one embodiment, initial preset assignment of broadcast radio stations is done automatically. Referring to FIG. 7, there is shown a flow diagram of a process for automatically initial preset assignment by a computer program running on computer system 20. In step 100, a locator is entered, for example, by a user entering a "zip code" using keyboard 44. In optional step 102, the user enters radio format preference or preferences (i.e. such as news, talk, type of music as discussed above). At step 104, the computer program directs AM/FM tuner 12 to scan the applicable broadcast frequency band for strong signals. At step 106, the strongest signals are compared to available stations based on the locator and information about available radio stations, as discussed above in the discussion of audio system mode operation. At step 108, the broadcast frequencies of the strongest signals are

108, the broadcast frequencies of the strongest signals are assigned by the computer program to the presets. If format preferences have been entered at optional step 102, the strongest signals for each of the selected formats may be assigned to the presets. The number of presets for each format is dependent on the number of presets available and the number of formats selected. For example, if the user has selected two formats and there are six presets available, the broadcast frequencies of the strongest three signals in each format are assigned to presets. If optional step 102 has not been performed, stations may be assigned to presets in other ways; for example, the strongest signal of each of the formats may be assigned to a preset, or the strongest signals, irrespective of format may be assigned to preset.

A user can enter control signals or data for controlling the operation of the sound system through three data/control input systems. A first input system includes the input devices of computer system 20, including mouse 40, keyboard 44, and external display 36. A second input system includes the buttons of control panel (FIG. 5) of sound reproduction device 10 of FIG. 1. A third input system includes the remote control device 17 of FIG. 1, shown in more detail in FIG. 8. In one implementation, different subsets of control signals and data input can be entered through each of the input systems. In this implementation the control panel (FIG. 5) has input buttons for the following control/data functions: four buttons 120 for entering control signals and data for

various clock-radio functions of sound reproduction device 10;
a sound reproduction device on/off switch 122; a broadcast
band selector button 124; an aux input selector 126; volume
control buttons 127; two tuning buttons 128; and preset
5 buttons 72a - 72f, discussed above. Remote control device
(FIG.8) has input buttons for the following control/data
functions: sound reproduction device on/off switch 130;
volume control buttons 134; broadcast band selector button
136; PC signal source selector buttons 138, preset selector
10 buttons 140a - 140f, CD player pause button 141; and five
``overloaded'' or multi-use buttons. Button 142 activates the
``snooze'' feature if the sound reproduction device has been
turned on to a broadcast radio station by the alarm, or mutes
or unmutes the sound reproduction device if the sound
15 reproduction device has been turned on any other way. Button
144 turn off the alarm if the clock radio alarm feature of the
sound reproduction device is sounding, or stops the CD player
28. Track/tune button 147 is discussed in more detail below.

Equivalent control signals that can be entered from more
20 than one of the three input systems have the same effect,
regardless of which input system was used to enter the data or
control signal. For example, if the sound source is FM
broadcast radio, and preset button 1 is activated, the audio
system tunes to the broadcast frequency represented by preset
25 button 1, regardless of whether the preset button was
activated by pressing preset button 72a on the control panel,
pressing preset button 140a, on remote control device 17, or

by selecting preset icon 150a on the user interface screen (FIG. 6) shown on display 36 (FIG. 1). Additionally, if the data or control signal is entered through remote control device 17 or through the sound reproduction device control panel (FIG. 5), a visible indication is displayed on the user interface screen (FIG. 6). For example, if preset button 140a (preset button 1) is pressed on remote control device 17, a visible indication appears on user interface screen (FIG. 6) shown on display 36.

The effect of the control signal may depend on the source of the audio signals. For example, if the source of the audio signals is the AM/FM tuner 12 (FIGS. 1 and 2), selecting the ``tuning'' buttons 128 (FIG. 5) on the control panel, or the corresponding buttons 147 (FIG. 8) on the remote control device, or the corresponding graphical figures 79 (FIG. 6) causes the tuning frequency of the AM/FM tuner to change. If the source is music files, the names of the music files may appear in the available selections region 90 (FIG. 6) of the interface screen, and selecting of the tuning buttons on the control panel or the equivalent control buttons on remote control device or the equivalent graphical figure on the display screen may cause the display to change the highlighted music file. If the source is web radio stations, the available web radio stations may appear in the available selections region 90 (FIG. 6) of the interface screen, and selecting of the tuning buttons on the control panel or the equivalent control buttons on remote control device or the

equivalent graphical figure on the display screen may cause the display to change the highlighted web radio station.

In the event that the control electronics circuitry 16 (FIG. 1) of the sound reproduction device receives from remote control device 17 a remote control signal that control electronics circuitry 16 cannot decode, the control electronics circuitry retransmits the remote control signal to computer system 20 for decoding.

For ease of selecting individual sources, in one embodiment, in addition to specifying a category (such as music files, broadcast radio stations, computer network accessible radio stations, music files, and CD) of sources, the user may select from a subset of all the sources in a category. For example, if the user has selected broadcast FM, broadcast AM, or network accessible radio as the source category, the user may choose to select an individual radio station from a subset of all available radio stations, the subset including only radio stations having a particular format, such as news; or if the user has selected music files as the source category the user may choose to select a file from a subset of all available files, the subset including only music of a certain type, such as jazz.

This may be conveniently done using the available selections region 90 (FIG. 6) and the various control input devices, including keyboard 44 or mouse 40 (FIGS. 1 and 2) radio control panel (FIG. 5), or the remote control device 17 (FIGS. 1, 2, and 8). The computer program running on computer

20 may provide for the user to enter a preferred subset category, or alternatively, may allow the user to sort, order or filter the entries in the available selections region. The input devices may then be used to highlight and select entries in the available selections region 90. In one embodiment, the tuning keys 128 of the control panel (FIG. 5), or the corresponding buttons 147 on remote control 17 are used to highlight and select entries in the available selections region. In this embodiment, pressing the tuning key 128 or 147 highlights the next entry in the available selections region 90. The tuning keys may also be used in the above manner even if the interface screen (FIG. 6) is not visible on the display, as may happen if the interface screen has been minimized or if the view of the interface screen is obscured by a graphical display generated by a software program. This aspect of the invention may also be used in audio systems which have no display associated with them.

In another embodiment, when the source category is broadcast radio, tuning keys 128 of the control panel (FIG. 5) and the corresponding buttons 147 on remote control 17 are used in the conventional manner, that is, to change the tuning frequency of AM/FM tuner 12.

FIGS. 9A, 9B, 9C and 9D are schematic circuit diagrams of circuitry in a radio in an exemplary embodiment of the invention implementing AM-FM tuner 16, audio signal processing circuit 14 and control electronic circuitry 16 in the system

of FIG. 2. FIG. 10 is a schematic circuit diagram of an exemplary embodiment of interface unit 54.

There is enclosed a CD-ROM that may be inserted into the D drive of a personal computer in an exemplary embodiment of the invention.

It is evident that those skilled in the art may make numerous modifications of and departures from the specific apparatus and techniques disclosed herein without departing from the invention concepts. Consequently, the invention is to be construed as limited only by the spirit and scope of the appended claims.

What is claimed is:

CLAIMS

1 1. An audio system comprising,
2 a sound reproduction device for producing audible sound
3 from audio signals including a radio tuner and a powered
4 speaker;

5 a connector for connecting said sound reproduction device
6 with a computer, said computer for providing audio signals
7 from a plurality of sources, said sources including a computer
8 CD player, digitally encoded computer files stored on said
9 computer, and a computer network connected to said computer;

10 said sound reproduction device further comprising control
11 buttons for controlling at least one of said computer CD
12 player, said digitally encoded computer files and said
13 computer network.

1 2. An audio system in accordance with claim 1, and further
2 comprising,

3 an interface device for connecting said computer and said
4 connector, said interface device comprising a digital to
5 analog converter.

1 3. An audio system in accordance with claim 1 wherein said
2 sound reproduction device is constructed and arranged to
3 produce audible sound from only analog audio signals.

1 4. An audio system in accordance with claim 3 wherein said
2 sound reproduction device is constructed and arranged to
3 receive digitally encoded control signals from said computer.

1 5. An audio system in accordance with claim 1 and further
2 comprising,
3 a remote control device for transmitting commands to said
4 sound reproduction device.

1 6. An audio system in accordance with claim 5 wherein said
2 sound reproduction system is constructed and arranged to
3 transmit said commands to said computer.

1 7. An audio system in accordance with claim 1 wherein said
2 radio tuner and said powered speaker are contained in a single
3 enclosure.

1 8. An audio system comprising,
2 a sound reproduction device for producing audible sound
3 from audio signals including an enclosure enclosing a radio
4 tuner and a powered speaker;
5 a connector for connecting said sound reproduction device
6 with a computer;
7 said computer for providing audio signals from a computer
8 CD player, from digitally encoded computer files, and from a
9 computer network; and

10 a remote control device for transmitting commands to said
11 sound reproduction device to control at least one of said
12 computer CD player, said digitally encoded computer files and
13 said computer network.

1 9. An audio system in accordance with claim 8 and further
2 comprising,

3 an interface device for connecting said computer and said
4 connector;

5 said interface device comprising a digital to analog
6 converter.

1 10. An audio system in accordance with claim 8 wherein said
2 sound reproduction device is constructed and arranged to
3 produce audible sound from exclusively analog encoded audio
4 signals and is not designed and constructed to produce audible
5 sound from digitally encoded audio signals.

1 11. An audio system in accordance with claim 8 and further
2 comprising a remote control device for transmitting commands
3 to said audio system.

1 12. An audio system in accordance with claim 11 wherein said
2 sound reproduction system is constructed and arranged to
3 transmit said commands to said computer.

1 13. An audio system comprising,

2 a sound reproduction device for reproducing, from audio
3 signals audible sound;

4 a computer coupled to said sound reproduction device for
5 receiving said audio signals from a computer network;

6 said audio signals being transmitted from an
7 alternatively selectable plurality of network addresses;

8 a remote control device for communicating commands to
9 said sound reproduction device and having a plurality of
10 indicator buttons;

11 wherein an indicating of a one of said indicator buttons
12 causes said computer to select a preassigned one of said
13 network addresses.

1 14. An audio system in accordance with claim 13 wherein said
2 computer is constructed and arranged for storing and
3 retrieving digitally encoded audio signals;

4 said digitally encoded audio signals being stored in said
5 computer in computer files characterized by a file name;

6 wherein said selector is for selecting said audio signals
7 from one of said computer network or said computer files;

8 wherein a selecting of said computer network causes said
9 indicating to cause said computer to select said preassigned
10 one of said network addresses; and

11 wherein a selecting of said computer files causes said
12 indicating to select a preassigned assemblage of said computer
13 files.

1 15. An audio system in accordance with claim 13 and further
2 comprising,

3 a radio tuner coupled to said sound reproduction device
4 for receiving broadcast audio signals,

5 said audio signals being transmitted on carrier waves of
6 a plurality of selectable frequencies;

7 a selector for selecting audio signals from one of said
8 computer network and said radio tuner for sound reproduction
9 by said sound reproduction device;

10 wherein a selecting of said computer network causes said
11 indicating to cause said computer to select said preassigned
12 one of said network addresses; and

13 wherein a selecting of said radio tuner causes said
14 indicating to cause said radio tuner to select a preassigned
15 one of said plurality of selectable frequencies.

1 16. An audio system in accordance with claim 15 wherein said
2 computer is constructed and arranged for storing and
3 retrieving digitally encoded audio signals,

4 said digitally encoded audio signals being stored in said
5 computer in computer files characterized by a file name;

6 wherein said selector is for selecting said audio signals
7 from one of said computer network, said radio tuner, and said
8 computer files;

9 wherein a selecting of said computer network causes said
10 indicating to cause said computer to select said preassigned
11 one of said network addresses;

12 wherein a selecting of said radio tuner causes said
13 indicating to cause said radio tuner to select a preassigned
14 one of said plurality of selectable frequencies; and

15 wherein a selecting of said computer files causes said
16 indicating to select a preassigned assemblage of said computer
17 files.

1 17. An audio system in accordance with claim 13 and further
2 comprising,

3 a plurality of mechanical buttons on said sound
4 reproduction device;

5 said mechanical buttons corresponding to said indicator
6 buttons on said remote control device; and

7 wherein a pressing of a mechanical button corresponding
8 to said indicator button causes said device to select said
9 one of said network addresses.

1 18. In an audio system comprising a computer system and a
2 sound reproduction system for reproducing audible sound from
3 audio signals, the audio signals coming from a plurality of
4 selectable sources, a method for switching said sound
5 reproduction system from an unpowered state to a powered state
6 comprising,

7 transmitting a control signal from said sound
8 reproduction system to said computer system; and

9 if said computer system responds to said control signal,
10 determining by said sound reproduction device that said
11 computer system is in a responsive state; and

12 if said computer system does not respond to said control
13 signal, determining by said sound reproduction device that
14 said computer system in an unresponsive state.

1 19. A method for switching a sound reproduction system from
2 an unpowered state to a powered state in accordance with claim
3 18 and further comprising,

4 responsive to a determination that said computer system
5 is unresponsive, selecting an audio signal source that is
6 accessible without said computer system.

1 20. In a radio receiver having a number n of preset
2 indicators, a method for assigning broadcast frequencies to
3 individual preset indicators, comprising,

4 determining the location of the radio receiver; and

5 scanning the frequency spectrum to determine the strength
6 of signals received and the corresponding frequency of said
7 received signals.

1 21. A method for assigning broadcast frequencies to preset
2 indicators in accordance with claim 20 and further comprising
3 assigning the n strongest signals to the n presets,
4 respectively.

1 22. A method for assigning broadcast frequencies to
2 individual preset indicators in accordance with claim 20 and
3 further comprising determining the broadcast format of the
4 radio stations.

1 23. A method for assigning broadcast frequencies to
2 individual preset indicators in accordance with claim 22 and
3 further comprising assigning the frequencies corresponding to
4 the $\frac{n}{m}$ strongest signals to the n presets for each of the
5 broadcast formats, where m is the number of formats.

1 24. A method for assigning broadcast frequencies to
2 individual preset indicators, in accordance with claim 22 and
3 further comprising,

4 determining the p user preferences for broadcast format,
5 where p is a number <n representing the number of user
6 preferences for broadcast formats; and

7 assigning the frequencies corresponding to the $\frac{n}{p}$
8 strongest signals in each of the preferred broadcast formats
9 to the n presets.

1 25. In a sound system comprising a sound reproduction device
2 coupled to a computer system and a remote control device for
3 transmitting encoded control commands to said sound
4 reproduction device, a method for decoding said encoded
5 control commands comprising,

6 receiving, by said sound reproduction device one of said
7 encoded control commands;

8 decoding by said sound reproduction device the encoded
9 control command;

10 executing by said sound reproduction device the encoded
11 control command;

12 in the event that said one received control command is
13 not decodable or is not executable by said sound reproduction
14 device, transmitting said encoded control command to said
15 computer system.

1 26. A sound system, comprising,

2 a sound reproduction device for reproducing sound from,
3 alternatively, broadcast radio audio signals and digitally
4 encoded audio signals transmitted to said sound reproduction
5 device from a computer,

6 said digitally encoded audio signals from one of a
7 plurality of sources that are selectable and indicatable on a
8 computer display device,

9 said sound reproduction device comprising a control
10 button for changing the tuning frequency to which said sound
11 reproduction device is tuned,

12 wherein said control button is constructed and arranged
13 to select said one source.

1 27. An audio system, comprising,

2 a sound reproduction device for reproducing, from
3 digitally encoded audio signals stored in alternatively
4 selectable plurality of digitally encoded files stored on a
5 digital storage device;

6 a plurality of individually indicatable preset
7 indicators;

8 wherein an indicating of a one of said preset indicators
9 causes said device to select for reproducing a preassigned one
10 of said digitally encoded files.

1 28. An audio system in accordance with claim 27, wherein said
2 indicating causes said device to select a preassigned
3 plurality of said digitally encoded files,

4 said audio system further comprising an order indicating
5 system for indicating an order in which said preassigned
6 plurality of computer files are reproduced,

7 said orders including a first order in which said
8 preassigned plurality of computer files are reproduced in a
9 predefined sequence and a second order in which said
10 preassigned plurality of computer files are reproduced in a
11 random sequence.

1 29. An audio system comprising,

2 a sound reproduction device for reproducing audible sound
3 from audio signals from a plurality of sources,

4 said sources including a radio tuner and at least one of
5 a CD containing a plurality of individually indicatable
6 tracks, a plurality of individually indicatable network
7 addresses, and a plurality of individually indicatable
8 digitally encoded files stored on a digital storage device;

9 a source selector, for selecting from said plurality of
10 sources a source of audio signals to be reproduced by said
11 sound reproduction device;

12 a control signal input device;

13 wherein in the event that said selected source is said
14 radio tuner, an activation of said control signal input device
15 changes the tuning frequency of said radio tuner;

16 in the event that said selected source is said CD, an
17 activation of said control signal input device changes the
18 indicated CD track; and

19 in the event that said selected source is said selectable
20 network addresses, an activation of said control signal device
21 changes the indicated network address.

1 30. A method of operating an audio system adapted to
2 reproduce sound from a plurality of digitally encoded files,
3 said files containing identifying characteristics, comprising,
4 assigning a value one of said identifying characteristics
5 to a preset indicator;

6 on the indicating of said preset indicator, searching
7 said plurality of files for said value of said one identifying
8 characteristic; and

9 selecting for reproduction the digitally encoded files
10 having said value.

1 31. A method of operating an audio system in accordance with
2 claim 30 wherein said identifying characteristics are recorded
3 in a data base and wherein said searching comprises searching
4 said data base for said one identifying characteristic.

1 32. A method for selecting from a plurality of records a
2 single record, said records having fields, comprising,

3 specifying a value of one of said fields;
4 determining, by a computer, which of said records have
5 said value for said one characteristic;
6 selecting a one of said records by entering a command on
7 an input device;
8 wherein said input device is a control panel of an
9 attached radio.

1 33. A method for selecting from a plurality of records a
2 single record in accordance with claim 32 and further
3 comprising,
4 presenting on a display a list,
5 said list having an entry corresponding to each of said
6 determined records.

1 34. A method for selecting records in accordance with claim
2 32 wherein said input device is a remote control device
3 associated with an attached radio.

1 35. A method for selecting audio records in accordance with
2 claim 32 wherein said input device comprises a tuning button
3 for tuning said attached radio and wherein said command is
4 entered by pressing said tuning button.

1 36. A method for selecting from a plurality of records a
2 single record, said records having fields, comprising,
3 presenting said records on a display in the form of a
4 list;

5 said list having an entry corresponding to each of said
6 records;

7 sorting said records so that entries having a common
8 value for one of said fields are successive entries in said
9 list;

10 highlighting on said display a one of said presented
11 records by entering a command on an input device;

12 wherein said input device is a control panel of an
13 attached radio.

1 37. A method for selecting records in accordance with claim
2 36 wherein said input device is a remote control device
3 associated with an attached radio.

1 38. A method for selecting audio records in accordance with
2 claim 36, wherein said input device comprises a tuning button
3 for tuning said attached radio and wherein said command is
4 entered by pressing said tuning button.

1 39. A method for selecting from a plurality of records a
2 single record, said records having fields, comprising,
3 ordering said records so that entries in said list are
4 ordered according to their respective values of one of the
5 fields;

6 selecting one of said presented records by entering a
7 first command on an input device;

8 wherein said input device is a control panel of an
9 attached radio; and

10 selecting an adjacent record by entering a second command
11 on said input device.

1 40. A method for selecting from a plurality of records a
2 single record in accordance with claim 39 and further
3 comprising,

4 presenting said records on a display in the form of a
5 list,

6 said list having an entry corresponding to each of said
7 records.

1 41. A method for selecting records in accordance with claim
2 39 wherein said input device is a remote control device
3 associated with an attached radio.

1 42. A method for selecting audio records in accordance with
2 claim 39 wherein said input device comprises a tuning button
3 for tuning said attached radio and wherein said command is
4 entered by pressing said tuning button.

1 43. A method of giving multiple sets of values to a single
2 set of presets being used with a single source with a system
3 including a computer having a screen display with graphics and
4 a pointing device, a radio having presets and a remote
5 associated with the radio having corresponding presets,
6 comprising,

7 using the pointing device to click on a graphic on the
8 screen display to bring up a new set of values for the presets

9 whereby any one of the set of values is selectable by using
10 the pointing device to click on a preset graphic on the screen
11 display, pressing the selected preset on the remote, or
12 pressing the preset on the radio.

002103-390001

ABSTRACT

An audio system attachable to a computer includes a sound reproduction device for producing audible sound from audio signals. The sound reproduction device includes a radio tuner and a powered speaker. The audio system further includes a connector for connecting the sound reproduction device with a computer. The computer provides audio signals from a plurality of sources, the sources including a computer CD player, digitally encoded computer files stored on the computer, and a computer network connected to the computer. The sound reproduction device further includes control buttons for controlling at least one of the computer CD player, the digitally encoded computer files and the computer network.

20090823.doc


[illegible]

Fig 1




FIG. 2




FIG. 3




FIG. 4

FIG. 5

79

88

92

90

BOSE
Wave Radio/PC

84.7 FM
WMA5
Unknown Format

Tune
Volume
20

AM FM
WDRING
Auto Play

Scan Memory ID#

Station Memory

Flag	Station ID	Frequency	Name	Memory	ID#
	WAAF	Unknown Format	Worcester, MA		
	WBCH	Unknown Format	Boston, MA		
	WBGL, Preset 4	Unknown Format	Boston, MA		
	WBOS	Unknown Format	Brookline, MA		
	WBUR	Unknown Format	Boston, MA		
	WCB	Unknown Format	Falmouth, MA		
	WCRB, Preset 5	Unknown Format	Waltham, MA		
(+)	WCTK, Preset 3	Unknown Format	New Bedford, MA		
	WDIM	Unknown Format	Framingham, MA		
	WEVO	Unknown Format	Concord, NH		
(+)	WGBH	Unknown Format	Boston, MA		
	WGIR	Unknown Format	Manchester, NH		
	WHEB	Unknown Format	Portsmouth, NH		
	WICN	Unknown Format	Worcester, MA		
	WJFD	Unknown Format	New Bedford, MA		
(+)	WJMN, Preset 2	Unknown Format	Boston, MA		
	WKLB	Unknown Format	Lowell, MA		

Add Station Delete Station Update Stations Set File Station Selection

79

88

92

90

FIG. 6




FIG. 7

17




FIG. 8

DATE		TIME		DATE		TIME	
01	10/15/75	08:00	08:00	02	10/15/75	08:00	08:00
02	10/15/75	08:00	08:00	03	10/15/75	08:00	08:00

9768		9769		9770		9771		9772		9773		9774		9775		9776		9777		9778		9779		9780		9781		9782		9783		9784		9785		9786		9787		9788		9789		9790		9791		9792		9793		9794		9795		9796		9797		9798		9799		9800		9801		9802		9803		9804		9805		9806		9807		9808		9809		9810		9811		9812		9813		9814		9815		9816		9817		9818		9819		9820		9821		9822		9823		9824		9825		9826		9827		9828		9829		9830		9831		9832		9833		9834		9835		9836		9837		9838		9839		9840		9841		9842		9843		9844		9845		9846		9847		9848		9849		9850		9851		9852		9853		9854		9855		9856		9857		9858		9859		9860		9861		9862		9863		9864		9865		9866		9867		9868		9869		9870		9871		9872		9873		9874		9875		9876		9877		9878		9879		9880		9881		9882		9883		9884		9885		9886		9887		9888		9889		9890		9891		9892		9893		9894		9895		9896		9897		9898		9899		9900		9901		9902		9903		9904		9905		9906		9907		9908		9909		9910		9911		9912		9913		9914		9915		9916		9917		9918		9919		9920		9921		9922		9923		9924		9925		9926		9927		9928		9929		9930		9931		9932		9933		9934		9935		9936		9937		9938		9939		9940		9941		9942		9943		9944		9945		9946		9947		9948		9949		9950		9951		9952		9953		9954		9955		9956		9957		9958		9959		9960		9961		9962		9963		9964		9965		9966		9967		9968		9969		9970		9971		9972		9973		9974		9975		9976		9977		9978		9979		9980		9981		9982		9983		9984		9985		9986		9987		9988		9989		9990		9991		9992		9993		9994		9995		9996		9997		9998		9999		10000		10001		10002		10003		10004		10005		10006		10007		10008		10009		10010		10011		10012		10013		10014		10015		10016		10017		10018		10019		10020		10021		10022		10023		10024		10025		10026		10027		10028		10029		10030		10031		10032		10033		10034		10035		10036		10037		10038		10039		10040		10041		10042		10043		10044		10045		10046		10047		10048		10049		10050		10051		10052		10053		10054		10055		10056		10057		10058		10059		10060		10061		10062		10063		10064		10065		10066		10067		10068		10069		10070		10071		10072		10073		10074		10075		10076</
------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	-------	--	---------




FIG 9C

09689397 at 101200

8x add
for mod power




FIG. 10

0908337 m 101200

Colomb
to produce

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant : Beckmann, et al. Art Unit : Not yet assigned
Serial No. : Not yet assigned Examiner : Not yet assigned
Filed :
Title : INTERACTIVE SOUND REPRODUCING

Hon. Commissioner for Patents
Washington, D.C. 20231

POWER OF ATTORNEY AND ELECTION OF ASSIGNEE
TO CONDUCT PROSECUTION

The undersigned, the owner of the entire right, title and interest in the above-identified application filed herewith, elects to exclusively conduct the prosecution of this application in accordance with the provisions of 37 C.F.R. § 3.71 and appoints as attorney of the undersigned

Charles Hieken
Reg. No. 18,411
FISH & RICHARDSON P.C.
225 Franklin Street
Boston, Massachusetts 02110-2804
Telephone: (617) 542-5070
Facsimile: (617) 542-8906

to prosecute said application and to transact all business in the Patent and Trademark Office connected therewith with full powers of substitution. Please send all correspondence and direct all telephone calls to the above attorney at the above address, telephone number and facsimile number.

CERTIFICATE OF MAILING BY EXPRESS MAIL

Label No.: EL624275964 US

I hereby certify under 37 CFR §1.8(a) that this correspondence is being deposited with the United States Postal Service as Express Mail Post Office to Addressee with sufficient postage on the date indicated below and is addressed to the Commissioner for Patents, Washington, D.C. 20231.

October 12, 2000
Date of Deposit

Samantha Bell
Signature

Samantha Bell
Typed or Printed Name of Person Signing Certificate

002707 22262960

Applicant : Beckmann, et al.
Serial No. : Not yet assigned
Filed :
Page : 2

Attorney's Docket No.: 02103-390001

BOSE CORPORATION

Date October 10, 2000

By Mark E. Sullivan
Name Mark E. Sullivan
Title Assistant Secretary

CPH/dmm

Fish & Richardson P.C.
225 Franklin Street
Boston, MA 02110-2804
Telephone: (617) 542-5070
Facsimile: (617) 542-8906

20057136.doc

002101 2228950